

D10 Bench Top Microlaser Driver



Parameter	Specification
AC Input Voltage	100-250 VAC, 1-phase or 2-phase, auto-switching
AC Input Frequency	50-60 Hz
AC Input Current	1.4 Arms for 115 VAC; 0.7 Arms for 230 VAC
AC Input Fuse	2 Amp, Type 239 (5x20mm, Slow-Blow)
External Fire Input BNC	4 – 12 V, 1 mS +/- 0.5 mS pulse, 0-10 Hz, 21 mA (560Ω load)
Operating Temperature	0°C to +50°C
Storage Temperature	-25°C to +85°C
Repetition Range	0.2 – 10 Hz
Pulse Width Range	1 -10 ms
Compliance Voltage	6 Volts
Current Range	0 -10 Amps

➤ For more information, contact sales@megawattlasers.com

The D10 micro-laser driver is designed to drive the MWL # ER902 Micro-laser. The D10 is very easy to setup and operate. Internal limits can be set for current, pulse width, and repetition rate, preventing possible laser damage.

